

# TURNOUT TEMPLATES

## For Micro Engineering HO #6 Turnouts

#14-705 HO Code 83 #6 LH      #14-805 HO Code 70 #6 LH  
#14-706 HO Code 83 #6 RH      #14-806 HO Code 70 #6 RH  
Scale: Actual size, but may not print to exact size.

### Turnout Specifications

- Frog angle: #6, 9.527°
- Turnout length: 10.857"
- Track center line radius: 34.6"
- Tie width: .094" (proto 8")
- Tie thickness: .078" (proto 7")
- Tie lengths: 1.157" - 2.261" (proto 8.5' - 16.5')
- Tie spacing: .226" (proto 20")
- Switch point throw: .073"

### Notes

- Templates are on 2" track centers.
- Turnouts have a sprung switch rail assembly.
- Turnouts are DCC compatible.

Cut out templates on lines

### Printing instructions

- This is an Adobe .pdf document and requires a program that can open and print pdf files such as Adobe Acrobat or Adobe Reader.
- Print this template on legal size paper (8½" x 14") in "Landscape" layout.
- Turn off all page scaling and fitting options.
- Although the drawings are actual size, they may not print to exact size depending on the specific printer and printer settings.
- After printing, confirm the size of your template with a ruler.

